## SOLAR PILING LITE – 8"

**MODEL: LL-SPL-WBA** 



120\*

Lumens

## SOLAR PILING LITES





**Lake Lite Inc.** 100 Industrial Dr. Avilla, IN 46710 Phone: 260-918-2758 E-mail: sales@lakelite.com Web: www.lakelite.com

Please Contact

	24-Ultra-High intensity LEDs (8-White, 8-Blue, 8-Amber) Adjustable with Magnet
	12/24/42/60/78/96/120 Lumens *Varies with Color & Brightness Settings
	White, Blue & Amber
	Constant
	1- 2+ Nautical Mile *Varies with LED color & Brightness Settings
	360°
)	100-180° *Various with Mounting
	> 100,000 hrs
ISTICS	
	Integrated
	3.2v
	16-20hrs *On full Charge * Varies With Brightness Settings & Conditions
	14-158° Fahrenheit
3	
	Multicrystalline or Monocrystalline
	2.2 watts
	16-17%
	High Capacity
	LiFePo4
	3000mA
	3.2v
	1-3 years (Varies with local Environment)
	Yes: User Changeable / Replaceable
ics	
	ASA Composite
	UV-Stabilized Polycarbonate
	Horizontal Lenticular
	Vertical Lenticular
	IP 68
	Fits on Pilings or flat surfaces 8" diameter and larger
	4-1/4"
	8"
	4 lbs
lors	Please Contact

Vertical Divergence (degrees) LED Life Expectancy (hours) ELECTRICAL CHARACTERISTICS Circuit Protection

Nominal Voltage (v) Autonomy (hours)

Temperature Range SOLAR CHARACTERISTICS Solar Module Type Power (watts)

Body Material Lens Material External Lens Design Internal Lens design Waterproof Rating Mounting Height Width / Diameter Weight OPTIONS

Solar Module Efficiency (%) POWER SUPPLY Battery Type Battery Size Battery Capacity (mAh) Nominal Voltage (v) Battery Service Life Battery Service Access PHYSICAL CHARACTERIST

Custom Options, Sizes, & Colo Custom Hardware & Mounting

\* Information subject to change without notice

LIGHT CHARACTERISTICS

Horizontal Output (degrees)

Light Source Lumens output Available LED Colors Light Mode Options Visible Range

## SOLAR PILING LITE – 8"



**MODEL: LL-SPL-WBA** 



**Caution! When plugging battery connectors STOP** together, align notches before connecting both connectors. Failure to do so could result in permanent damage to the light.

#### **Battery Information**

### LiFePo4 Type Battery:

#### Volts: 3.2v Cell Size: 18500 Capacity: 3000mA

**DO NOT USE:** standard 1.2v NiMh or NiCd type Rechargeable batteries, or they will be damaged!



#### **BATTERY MAINTENANCE**

#### For prolonged storage when not using the product please follow these procedures.

- 1. Charge Batteries inside product on sunny day
- 2. Before Nightfall open your light and FULLY Disconnect the battery from the product
- 3. Store Battery and Product in warm/dry location.
- 4. Note: Batteries can be damaged from sub-zero temperatures when not in use.

CAUTION: PLEASE KEEP OUR ENVIORNMENT CLEAN! BATTERIES MUST BE RECYCLED OR DISPOSED OF PROPERLY.

#### Mounting Hardware Suggestions – Not Included

Mount Type	Hardware	Stainless Steel Recommended
No Through Hole	#14 OVAL HEAD Screws x Desired Length	
No Through Hole	5/16" Lag Bolts x Necessary Length with 5/16" Washers	
No Through Hole	3/8" Lag Bolts x necessary Length with 3/8" Washers	
Through Hole	5/16" Bolts X Necessary Length with 5/16" Washers & 5/16" Nuts	
Through Hole	3/8" Bolts X Necessary Length with 3/8" Washers & 3/8" Nuts	



Lake Lite Inc. 100 Industrial Dr. Avilla, IN 46710

Phone: 260-918-2758 E-mail: sales@lakelite.com www.lakelite.com Web:



80%	7-9 hrs
65%	10-12 hrs
50%	13-14 hrs
35%	15-17hrs
20%	17-22 hrs
OFF	OFF
Holding for 5-seconds	Changes LED color

\* Note: Run times will vary significantly based on factors such as; Sun Exposure, Season, Geographic Location, Shading, Installed Location/Position, Battery Condition, Brightness Setting, etc... The following run times should only be used as a general reference and are not guaranteed. Consider your local environment.

# Panel **NOTE:** moving too slowly may

0

activate the magnet switch multiple times going through multiple levels at once. A quick motion will help!

**CHANGING LED COLORS** Hold the magnet over the activation area for 5 seconds until the LED color changes

Change brightness/power level at night by waving the magnet over the solar panel

Holding the magnet for 5-seconds in the activation area will change to the next LED color. You may then change between brightness/power levels on that LED color.



3

Lake Lite Inc. 100 Industrial Dr. Avilla, IN 46710

4

Phone: 260-918-2758 E-mail: sales@lakelite.com www.lakelite.com Web:

## SOLAR PILING LITE – 8"

**MODEL: LL-SPL-WBA** 

T 1 **Top Screws** Top 3.2v LiFePo4 3000mA Seal Silicone Pad Lens **Battery Cover Cover Screws** Base 5 Use the provided wrench and screws to secure the silicone 6 Use Provided wrench and top screws to assembly your pad and battery cover. Fully tighten screws to ensure the light together. NOTE: The seal must be in the correct position before tightening down the top to the base. chamber is waterproof. Mounting Screws Screwdriver Wood Piling Wood Piling 8 Place light onto piling and mark holes. Drill small pilot holes Verify that the top screws are tight to provide a good seal in piling with drill bit. Use screwdriver to secure the light to for the lens. Verify that the base of the light is secured to your piling with mounting screws - Not Included the piling. Phone:



**Lake Lite Inc.** 100 Industrial Dr. Avilla, IN 46710 Phone: 260-918-2758 E-mail: sales@lakelite.com Web: www.lakelite.com

(LAKE LITE



#### **Owner Registration Card**

Please fill out and affix proper postage and return this owner registration card **within 10 days** to ensure that your new Solar Piling Light is covered by the limited warranty.

Purchaser's Name	<u> </u>
Address	<u>.</u>
State	Zip
Purchase Date:	Number of Lights:
Where Purchased (Store Name	e):
Model No.	LL-SPL-WBA
UPC No.	Varies On Different
Models	

#### Lake Lite Inc. 1-Year Limited Warranty

The retailer warrants the Solar Light to be free from defects in workmanship and material present at time of shipment from the factory for a period of one year after the date of purchase by the original purchaser. We agree to correct such defects without charge or at our option replace with a comparable or superior model if the product is returned to the retailer. To obtain warranty service, you must present a copy of the receipt as proof of purchase. All costs of removing and reinstalling the product are your responsibility. Damage to any part such as by accident or misuse or improper installation or by affixing any accessories, is not covered by this warranty. There is no other express warranty. The retailer hereby disclaims any and all warranties, including but not limited to, those of merchantability and fitness for a particular purpose to the extent permitted by law. The duration of any implied warranty, which cannot be disclaimed, is limited to the time period as specified in the express warranty. Some states do no allow limitation on how long an implied warranty lasts, so the above limitation may not apply to you. The retailer shall not be liable for incidental, consequential, or special damages arising out of or in connection with product use or performance except as may otherwise be accorded by law. Some states do not allow the exclusion of incidental or consequential damage, so the above exclusion or limitation may apply to you. This warranty gives specific legal rights, and you may also have other rights, which vary from state to state. This warranty supersedes all prior warranties.

Lake Lite Inc. 100 Industrial Dr. Avilla, IN 46710



**Lake Lite Inc.** 100 Industrial Dr. Avilla, IN 46710 Phone: 260-918-2758 E-mail: sales@lakelite.com Web: www.lakelite.com